

AURORA recessed emergency light with UPS, Anti-panic lighting, Non-maintained, 4000K, LED2, 250 lumens, 3W, White

About Product

AURORA emergency light is designed and manufactured by Mazinoor with different lens options for providing enough light in case of power outage or escape pathway emergency lighting.




Technical Information



AURORA recessed emergency light with UPS, Anti-panic lighting, Non-maintained, 4000K, LED2, 250 lumens, 3W, White

Photometric Graph



Ceiling		70	70	50	50	30	70	70	50	50	30
Walls		50	30	50	30	30	50	30	50	30	30
ρ Floor		20	20	20	20	20	20	20	20	20	20
Room Size X Y		Viewing direction at right angles to lamp axis					Viewing direction parallel to lamp axis				
2H	2H	17.8	19.5	18.2	19.8	20.0	17.8	19.5	18.2	19.8	20.0
	3H	18.5	20.0	18.9	20.3	20.6	18.5	20.0	18.9	20.3	20.6
	4H	18.5	19.9	18.9	20.2	20.6	18.5	19.9	18.9	20.2	20.6
	6H	18.5	19.8	18.8	20.1	20.4	18.5	19.8	18.8	20.1	20.4
	8H	18.4	19.7	18.8	20.0	20.3	18.4	19.7	18.8	20.0	20.3
	12H	18.4	19.6	18.8	19.9	20.3	18.4	19.6	18.8	19.9	20.3
4H	2H	18.4	19.8	18.8	20.1	20.4	18.4	19.8	18.8	20.1	20.4
	3H	19.1	20.3	19.5	20.7	21.0	19.1	20.3	19.5	20.7	21.0
	4H	19.2	20.2	19.6	20.6	21.0	19.2	20.2	19.6	20.6	21.0
	6H	19.1	20.1	19.6	20.4	20.8	19.1	20.1	19.6	20.4	20.8
	8H	19.1	20.0	19.5	20.4	20.8	19.1	20.0	19.5	20.4	20.8
	12H	19.1	19.8	19.5	20.3	20.7	19.1	19.8	19.5	20.3	20.7
8H	4H	19.1	20.0	19.6	20.4	20.8	19.1	20.0	19.6	20.4	20.8
	6H	19.1	19.8	19.6	20.2	20.7	19.1	19.8	19.6	20.2	20.7
	8H	19.1	19.7	19.6	20.2	20.6	19.1	19.7	19.6	20.2	20.6
	12H	19.1	19.6	19.6	20.1	20.6	19.1	19.6	19.6	20.1	20.6
12H	4H	19.1	19.9	19.6	20.3	20.7	19.1	19.9	19.6	20.3	20.7
	6H	19.1	19.7	19.6	20.1	20.6	19.1	19.7	19.6	20.1	20.6
	8H	19.1	19.6	19.6	20.1	20.6	19.1	19.6	19.6	20.1	20.6
ariation of t	he observer	position I	for the lum	inaire dista	ances S						
S = 1.0H		+0.4 / -0.3					+0.4 / -0.3				
S = 1.5H		+1.4 / -1.5				+1.4 / -1.5					
S = 2.0H		+2.1 / -3.5					+2.1 / -3.5				
Standard table		BK02					BK02				
Correction Summand		1.6					1.6				

Dimensional Drawing

